

# Solo Uno

Streamer with built-in amplifier

**ARCAM**  
by HARMAN

The Solo Uno brings total simplicity to the complex world of audio streaming by providing a compact, stylish and elegant streamer with a built-in amplifier. Boasting the class-leading Arcam sound quality, the effortless system requires just two speakers, the Solo Uno and a mobile device using the native music app of choice via Apple Airplay2 or Google Chromecast. In addition, the Solo Uno can be updated “over the air” automatically to provide enhanced future streaming features and years of listening enjoyment.



## Features

- Class leading super-efficient amplifier design
- Stylish cast aluminium case
- A simple system that only requires two speakers, the Solo Uno and an app
- GoogleCast, Airplay 2, uPnP Streamer
- Optimised for low noise and minimum distortion
- High-end audio circuitry
- Subwoofer out

## Specifications

Frequency Response	10Hz – 20kHz	
Signal-to-Noise-Ratio (A-Weighted)	117dB	
Output Power (1kHz, 1% THD, Two channels driven)	4kΩ	50W
	8kΩ	25W
AUX Input sensitivity	2V	
Subwoofer	Output Level	2.1V
	Cross-over frequency	80Hz
Wireless network	802.11a/b/g/n/ac (2.4GHz/5GHz)	
2.4G Wi-Fi transmitter frequency range	2412 – 2472MHz (2.4GHz ISM Band, USA 11 Channels, Europe and others 13 Channels)	
2.4G Wi-Fi transmitter power	<20dBm	
2.4G Wi-Fi modulation	DBPSK, DQPSK, CCK, QPSK, BPSK, 16QAM, 64QAM	
5G Wi-Fi transmitter frequency range	5.150~5.350GHz, 5.470~5.725GHz, 5.725~5.825GHz	
5G Wi-Fi transmitter power	<23dBm	
5G Wi-Fi modulation	DBPSK, DQPSK, CCK, QPSK, BPSK, 16QAM, 64QAM, 256QAM	
Power requirements	100 - 240VAC, 50/60Hz	
Dimensions W x H x D (including speaker terminals)	140 x 52 x 213mm	
Net Weight	1.5kg	
Supplied accessories	Power cord Wi-Fi antenna User manual and registration card	